

VHF CAVITY SPLITTER

Characteristic & Application

- ◆ Working Band: 136 - 220MHz
- ◆ Cavity structure
- ◆ Low insertion loss: 0.3dB
- ◆ Operate in all frequency band



	2-Way PD1320-2N	3-Way PD1320-3N
Working Frequency Band(MHz)	136-220	136-220
Split Loss (dB)	3.0	4.8
Isolation Loss (dB)	0.3	0.3
Input Return Loss (dB)	20	20
Input Power (W)	250	250
Port Impedance (Ω)	50	50
Port to Port Isolation($\geq$ dB)	5	5
Connectors Type	N-F	N-F
Dimensions Size (cm) L*W*H	35*25*25	45*25*25

