

Currens Switching Power Supply. AV-6000 series



Technical Specification

Model	AV-6035	AV-6045
AC Input Voltage	Switch Option: 115VAC or 230VAC	
DC Output Voltage	Variable : 11VDC ~ 16VDC	
Output Current (Peak)	35 AMP	45 AMP
(Continuous)	30 AMP	40 AMP
Ripple Noise	17mV	17mV
LED Indicator(s)	Power ON : GREEN (Normal) Output over 17VDC: RED (Warning Alert)	
Fuse	220V/5A	220V/6A
Other Feature(s)	Auto Re-set, Short Circuit, Over-load and Over-Voltage Protection. Auto Cooling Fan.	
DC output connection terminal	Screw type x 2. Clip-On x 2.	
Dimension (mm)	L 240 x W 250 x H 150	
Weight (KG)	Approx. 3 KG	Approx. 3.5 KG

Technical Specification

Model	AV-6055	AV-6065
AC Input Voltage	Switch Option: 115VAC or 230VAC	
DC Output Voltage	Variable : 11VDC ~ 16VDC	
Output Current (Peak)	55 aMP	65 AMP
(Continuous)	47 AMP	55 AMP
Ripple Noise	17mV	17mV
LED Indicator(s)	Power ON : GREEN (Normal) Output over 17VDC: RED (Warning Alert)	
Fuse	220V/8A	220V/10A
Other Feature(s)	Auto Re-set, Short Circuit, Over-load and Over-Voltage Protection. Auto Cooling Fan.	
DC output connection terminal	Screw type x 2. Clip-On x 2.	
Dimension (mm)	L 240 x W 250 x H 150	
Weight (KG)	Approx. 4 KG	Approx. 4.5 KG